User Manual
AFRA AEGIS ROYAL LUXARY SAFE
AF-BS4000E

Entering Management Mode

Locate the setup button on the back of the door. Press and release it immediately. Follow the voice prompts to enter the admin password (default: 123456) and press the “#” key to confirm. You will then enter the system menu.

Menu Index

① **Set User Password** – Press “1”

Enter a 3-8 digit user password and press “#” to confirm. Re-enter the same password as prompted.

② **Add Fingerprint** – Press “2”

When the fingerprint scanner lights up, place your finger on it repeatedly until the light turns off, indicating successful registration.

③ **Delete Fingerprint** – Press “3”

This will clear all stored fingerprints.

④ **Set Admin Password** – Press “4”

Enter a 3-8 digit admin password and press “#” to confirm. Re-enter the same password as prompted.

⑤ **Set Door Opening Mode** – Press “5”

- **Standard Mode** – Press “1”
  Unlock the door with a key plus any electronic verification (password or fingerprint).
- **Security Mode** – Press “2”
  Requires pre-registered fingerprints to activate.

⑥ **Configure WiFi** – Press “6”

Ensure strong network signal and sufficient battery. Follow prompts in the Tuya app to complete setup.

⑦ **Set Face Recognition** – Press “7”

Register facial data directly via the system.

Authentication Modes

Security Mode requires dual verification:

- Password + Fingerprint
- Password + Face
- Face + Fingerprint

Key Notes:

1. Changing the password invalidates existing fingerprints/face data. Security Mode cannot be activated.
2. Changing fingerprints retains the original password. Face verification fails; switch to Password + Fingerprint for Security Mode.
3. Changing face data retains the original password. Fingerprint verification fails; password must be used first.
4. If both face and fingerprint are registered, Security Mode accepts: Password + Fingerprint, Password + Face, or Face + Fingerprint.

Single-Mode Settings:

1. Setting a password disables fingerprints/face.
2. Adding a fingerprint disables face recognition.
3. Adding face data disables fingerprints.

Factory Reset

Press and hold the setup button for over 5 seconds until the voice prompt announces, “Factory reset successful.”